

AT24C32/CAT24C32

AT24C32/CAT24C64

32K bits (4096 X 8) / 64K bits (8192 X 8) Two-wire Serial EEPROM

Features

- Two-wire Serial Interface
- ➤ VCC = 1.8V to 5.5V
- > Bi-directional Data Transfer Protocol
- Internally Organized
 AT24C32,/CAT24C32 4096 X 8 (32K bits)
 AT24C64,/CAT24C64 8192 X 8 (64K bits)
- > 400 kHz (1.8V, 2.7V,5V) Compatibility
- > 32-byte Page (32K/64K) Write Modes
- Partial Page Writes Allowed
- Self-timed Write Cycle (5 ms max)
- High-reliability
- > 1 Million Write Cycles guaranteed
- Data Retention > 100 Years
- > Operating Temperature: -40 to +85
- > 8-lead PDIP, 8-lead SOP and 8-lead TSSOP Packages
- ۶

Pin Configuration



Description

24C32/24C64 provides 32768/

65536 bits of serial electrically erasable and programmable read-only memory (EEPROM) organized as 4096 words of 8 bits each. The device is optimized for use in many industrial and commercial applications where low-power and low-voltage operations are essential. The AT24C32/AT24C64 is available in space-saving 8-lead PDIP, 8-lead SOP, and 8-lead TSSOP packages and is accessed via a two-wire serial interface.



Example

迦묵	封装	私印	工作电压	兼容电压
AT24C32C-PU-TUDI	DIP8	24C32C-PU	1.7to 5.5	
AT24C32D-XHM-T-TUDI	TSSOP8	24C32D	1.7to 5.5	
CAT24C32YI-GT3-TUDI	TSSOP8	C32F	1.7to 5.5	2 . 7 v
AT24C32D-STUM-T-TUDI	S0T23-5	BDMU	1.7to 5.5	
CAT24C32WI-GT3-TUDI	SOP8	24C32F	1.7to 5.5	
AT24C32D-SSHM-T-TUDI	SOP8	32DM	1.7to 5.5	2. 7 v
AT24C64C-PU-TUDI	DIP8	24C64C-PU	1.7to 5.5	
AT24C64D-XHM-T-TUDI	TSSOP8	24C64D	1.7to 5.5	
CAT24C64YI-GT3-TUDI	TSSOP8	C64F	1.7to 5.5	2 . 7v
CAT24C64WI-GT3-TUDI	SOP8	24C64F	1.7to 5.5	
AT24C64D-SSHM-T-TUDI	SOP8	64DM	1.7to 5.5	2 . 7v

Pin Descriptions

Pin number	Designation	Туре	Name and Functions
1 – 3	A0 - A2	I	Address Inputs DEVICE/PAGE ADDRESSES (A2, A1, A0) : The A2, A1 and A0 pins are device address inputs that are hardwired or left not connected for hardware compatibility with other 24 Cxx devices. When the pins are hardwired, as many as eight 32 K/64K devices may be addressed on a single bus system (device addressing is discussed in detail under the Device Addressing section). If the pins are left floating, the A2, A1 and A0 pins will be internally pulled down to GND if the capacitive coupling to the circuit board VCC plane is <3 pF. If coupling is >3 pF, recommends connecting the address pins to GND.
5	SDA	I/O & Open-dr ain	Serial Data SERIAL DATA (SDA): The SDA pin is bi-directional for serial data transfer. This pin is open-drain driven and may be wire-ORed with any number of other open-drain or open- collector devices.
6	SCL	I	Serial Clock Input SERIAL CLOCK (SCL): The SCL input is used to positive edge clock data into each EEPROM device and negative edge clock data out of each device.
7	WP	I	Write Protect WRITE PROTECT (WP): The write protect input, when connected to GND, allows normal write operations. When WP is connected high to VCC, all write operations to the memory are inhibited. If the pin is left floating, the WP pin will be internally pulled down to GND if the capacitive coupling to the circuit board VCC plane is <3 pF. If coupling is >3 pF, recommends connecting the pin to GND. Switching WP to VCC prior to a write operation creates a software write protect function. The write protection feature is enabled and operates as shown in the following Table 1 .
4	GND	P	Ground
8	VCC	P	Power Supply

Table 1: Write Protect

	Part of the Array Protected				
WP PIn Status:	24C32	24C64			
At VCC	Full (32K) Array	Full (64K) Array			
At GND	Normal Read/Write Operations				



Block Diagram



Functional Description

1. Memory Organization

24C32, 32K SERIAL EEPROM: The 32K is internally organized as 128 pages of 32 bytes each. Random word addressing requires a 12-bit data word address.

24C64, 64K SERIAL EEPROM: The 64K is internally organized as 256 pages of 32 bytes each. Random word addressing requires a 13-bit data word address.

2. Device Operation

CLOCK and DATA TRANSITIONS: The SDA pin is normally pulled high with an external device. Data on the SDA pin may change only during SCL low time periods (see Figure 1). Data changes during SCL high periods will indicate a start or stop condition as defined below.



START CONDITION: A high-to-low transition of SDA with SCL high is a start condition which must precede any other command (see Figure 2).

STOP CONDITION: A low-to-high transition of SDA with SCL high is a stop condition. After a read sequence, the stop command will place the EEPROM in a standby power mode (see Figure 2)

ACKNOWLEDGE: All addresses and data words are serially transmitted to and from the EEPROM in 8-bit words. The EEPROM sends a "0" to acknowledge that it has received each word. This happens during the ninth clock cycle.

STANDBY MODE: The 24C32/24C64 features a low-power standby mode which is enabled: (a) upon power-up and (b) after the receipt of the STOP bit and the completion of any internal operations

MEMORY RESET: After an interruption in protocol, power loss or system reset, any two-wire part can be reset by following these steps:

- 1. Clock up to 9 cycles.
- 2. Look for SDA high in each cycle while SCL is high.
- 3. Create a start condition.





Figure 2. Start and Stop Definition





Figure 3. Output Acknowledge



3. Device Addressing

The 32K/64K EEPROM devices all require an 8-bit device address word following a start condition to enable the chip for a read or write operation (see Figure 4).

The device address word consists of a mandatory "1", "0" sequence for the first four most significant bits as shown. This is common to all the Serial EEPROM devices.

The 32K/64K uses the three device address bits A2, A1, A0 to allow as many as eight devices on the same bus. These bits must compare to their corresponding hardwired input pins. The A2, A1, and A0 pins use an internal proprietary circuit that biases them to a logic low condition if the pins are allowed to float.

The eighth bit of the device address is the read/write operation select bit. A read operation is initiated if this bit is high and a write operation is initiated if this bit is low.

Upon a compare of the device address, the EEPROM will output a "0". If a compare is not made, the chip will return to a standby state.

NOISE PROTECTION: Special internal circuitry placed on the SDA and SCL pins prevent small noise spikes from activating the device.

DATA SECURITY: The 24C32/24C64 has a hardware data protection scheme that allows the user to write protect the entire memory when the WP pin is at VCC.

4. Write Operations

BYTE WRITE: A write operation requires an 8-bit data word address following the device address word and acknowledgment. Upon receipt of this address, the EEPROM will again respond with a "0" and then clock in the first 8-bit data word. Following receipt of the 8-bit data word, the EEPROM will output a "0" and the addressing device, such as a microcontroller, must terminate the write sequence with a stop condition. At this time the EEPROM enters an internally timed write cycle, t_{wR}, to the nonvolatile memory. All inputs are disabled during this write cycle and the EEPROM will not respond until the write is complete (see Figure 5).





PAGE WRITE: The 32K/64K devices are capable of 32-byte page writes.

A page write is initiated the same as a byte write, but the microcontroller does not send a stop condition after the first data word is clocked in. Instead, after the EEPROM acknowledges receipt of the first data word, the microcontroller can transmit up to 31 more data words. The EEPROM will respond with a "0" after each data word received. The microcontroller must terminate the page write sequence with a stop condition (see Figure 6).

The data word address lower five (32K/64K) bits are internally incremented following the receipt of each data word. The higher data word address bits are not incremented, retaining the memory page row location. When the word address, internally generated, reaches the page boundary, the following byte is placed at the beginning of the same page. If more than 32 data words are transmitted to the EEPROM, the data word address will "roll over" and previous data will be overwritten.

ACKNOWLEDGE POLLING: Once the internally timed write cycle has started and the EEPROM inputs are disabled, acknowledge polling can be initiated. This involves sending a start condition followed by the device address word. The read/write bit is representative of the operation desired. Only if the internal write cycle has completed will the EEPROM respond with a "0", allowing the read or write sequence to continue.

5. Read Operations

Read operations are initiated the same way as write operations with the exception that the read/write select bit in the device address word is set to "1". There are three read operations: current address read, random address read and sequential read.

CURRENT ADDRESS READ: The internal data word address counter maintains the last address accessed during the last read or write operation, incremented by one. This address stays valid between operations as long as the chip power is maintained. The address "roll over" during read is from the last byte of the last memory page to the first byte of the first page. The address "roll over" during write is from the last byte of the cur- rent page to the first byte of the same page.

Once the device address with the read/write select bit set to "1" is clocked in and acknowledged by the EEPROM, the current address data word is serially clocked out. The microcontroller does not respond with an input "0" but does generate a following stop condition (see Figure 7).

RANDOM READ: A random read requires a "dummy" byte write sequence to load in the data word address. Once the device address word and data word address are clocked in and acknowledged by the EEPROM, the microcontroller must generate another start condition. The microcontroller now initiates a current address read by sending a device address with the read/write select bit high. The EEPROM acknowledges the device address and serially clocks out the data word. The microcontroller does not respond with a "0" but does generate a following stop condition (see Figure 8).

SEQUENTIAL READ: Sequential reads are initiated by either a current address read or a random address read. After the microcontroller receives a data word, it responds with an acknowledge. As long as the EEPROM receives an acknowledge, it will continue to increment the data word address and serially clock out sequential data words. When the memory address limit is reached, the data word address will "roll over" and the sequential read will continue. The sequential read operation is terminated when the microcontroller does not respond with a "0" but does generate a following stop condition (see Figure 9)

Figure 4. Device Address





Figure 5. Byte Write



Figure 6. Page Write



Figure 7. Current Address Read



Figure 8. Random Read



Figure 9. Sequential Read





Electrical Characteristics

Absolute Maximum Stress Ratings

DC Supply Voltage0.3V to +6.5V
Input / Output VoltageGND-0.3V to Vcc+0.3V
Operating Ambient Temperature40 $^{\circ}\text{C}$ to +85 $^{\circ}\text{C}$
Storage Temperature

Comments

Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to this device. These are stress ratings only. Functional operation of this device at these or any other conditions above those indicated in the operational sections of this specification is not implied or intended. Exposure to the absolute maximum rating conditions for extended periods may affect device reliability.

DC Electrical Characteristics

Applicable over recommended operating range from: TA = -40 °C to +85 °C, Vcc = +1.8V to +5.5V (unless otherwise noted)							
Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition	
Supply Voltage	Vcc	1.8	-	5.5	V		
Supply Current Vcc = 5.0V	lcc1	-	0.4	1.0	mA	READ at 100 kHz	
Supply Current Vcc = 5.0V	lcc2	-	2.0	3.0	mA	WRITE at 100 kHz	
Standby Current	lsв	-	-	1.0	μΑ	V _{IN} = V _{cc} or GND	
Input Leakage Current	lu	-	-	3.0	μA	V _{IN} = Vcc or GND	
Output Leakage Current	llo	-	0.05	3.0	μΑ	Vout = Vcc or GND	
Input Low Level	Vil	-0.6	-	Vcc X 0.3	V		
Input High Level	Vн	Vcc X 0.7	-	Vcc + 0.5	V		
Output Low Level Vcc =5.0V	Vols	-	-	0.4	V	lo∟ = 3.0 mA	
Output Low Level Vcc =3.0V	Vol2	-	-	0.4	V	loL = 2.1 mA	
Output Low Level Vcc =1.8V	Vol1	-	-	0.2	V	loL = 0.15 mA	

Pin Capacitance

Applicable over recommended operating range from T_A = 25 °C, f = 1.0 MHz, Vcc = +1.8V

Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition
Input/Output Capacitance (SDA)	Ci/o	-	-	8	pF	V _{1/0} = 0V
Input Capacitance (A0, A1, A2, SCL)	Cin	-	-	6	pF	$\lor_{iN} = 0 \lor$





AC Electrical Characteristics

Applicable over recommended operating range from $T_A = -40$ C to +85 C, VCC = +1.8V to +5.5V, CL = 1 TTL Gate and 100 pF (unless otherwise noted)

Parameter	Symbol	1.8,	Unite		
		Min.	Тур.	Max.	Units
Clock Frequency, SCL	f _{SCL}	-	-	400	kHz
Clock Pulse Width Low	t _{LOW}	1.2	-	-	μs
Clock Pulse Width High	t _{HIGH}	0.6	-	-	μs
Noise Suppression Time	tı	-	-	50	ns
Clock Low to Data Out Valid	t _{AA}	0.1	-	0.9	μs
Time the bus must be free before a new transmission can start	t _{buf}	1.2	-	-	μs
Start Hold Time	t _{hd.sta}	0.6	-	-	μs
Start Setup Time	t _{su.sta}	0.6	-	-	μs
Data In Hold Time	t _{hd.dat}	0	-	-	μs
Data In Setup Time	t _{su.dat}	100	-	-	ns
Inputs Rise Time	t _R	-	-	0.3	μs
Inputs Fall Time	t _F	-	-	300	ns
Stop Setup Time	t _{su.sтo}	0.6	-	-	μs
Data Out Hold Time	t _{DH}	50	-	-	ns
Write Cycle Time	t _{wR}	-	-	5	ms
5.0V, 25 C, Byte Mode	Enduran ce	1M	-	-	Write Cycles

Bus Timing

Figure 10. SCL: Serial Clock, SDA: Serial Data I/O





Write Cycle Timing

Figure 11. SCL: Serial Clock, SDA: Serial Data I/O



重要通知与免责声明

深圳市钍地半导体有限公司将准确可靠地提供技术和可靠性数据(包括数据表)、设计资源 (包 括参考设计)、应用或其他设计建议、WEB工具、安全信息和其他资源,但不保证任何缺陷, -切 以实物测试为准,并且不作任何明示或暗示的保证,包括但不限于对适销性的暗示保证、对特 定 目的适用的暗示保证或不侵犯任何第三方知识产权的暗示保证。 这些资源旨在为使用钍地产品的熟练开发人员提供支持: (1) 为您的应用程序选择合适的产 品; (2) 设计、验证和测试您的应用程序; (3) 确保您的应用程序符合适用的标准和任何其他安 全 安保或其他要求; (4) 钍地和钍地标志是钍地半导体的注册商标。所有商标均为其各自所有 者的 财产;(5)有关更改详情,请查阅任何修订文件中包含的修订历史记录。资源可能会在不通 知的 情况下更改。我公司将不对使用此产品及其使用而导致的专利或第三方知识产权的侵权负责



24C32/64

Package Information

PDIP Outline Dimensions



重要通知与免责声明

深圳市钍地半导体有限公司将准确可靠地提供技术和可靠性数据(包括数据表)、设计资源 (包 括参考设计)、应用或其他设计建议、WEB工具、安全信息和其他资源,但不保证任何缺陷,一 切 以实物测试为准,并且不作任何明示或暗示的保证,包括但不限于对适销性的暗示保证、对特 定 目的适用的暗示保证或不侵犯任何第三方知识产权的暗示保证。 这些资源旨在为使用钍地产品的熟练开发人员提供支持:(1)为您的应用程序选择合适的产品

(2)设计、验证和测试您的应用程序;(3)确保您的应用程序符合适用的标准和任何其他安全、 安保或其他要求;(4)钍地和钍地标志是钍地半导体的注册商标。所有商标均为其各自所有者的 财产;(5)有关更改详情,请查阅任何修订文件中包含的修订历史记录。资源可能会在不通知 的 情况下更改。我公司将不对使用此产品及其使用而导致的专利或第三方知识产权的侵权负责



JEDEC SOIC





24C32/64

TSSOP



重要通知与免责声明

深圳市牡地半导体有限公司将准确可靠地提供技术和可靠性数据(包括数据表)、设计资源(包 括参考设计)、应用或其他设计建议、WEB工具、安全信息和其他资源,但不保证任何缺陷,一切 以实物测试为准,并且不作任何明示或暗示的保证,包括但不限于对适销性的暗示保证、对特定 目的适用的暗示保证或不侵犯任何第三方知识产权的暗示保证。 这些资源旨在为使用钍地产品的熟练开发人员提供支持: (1)为您的应用程序选择合适的产品; (2)设计、验证和测试您的应用程序; (3)确保您的应用程序符合适用的标准和任何其他安全、 安保或其他要求; (4)钍地和钍地标志是钍地半导体的注册商标。所有商标均为其各自所有者的 财产; (5)有关更改详情,请查阅任何修订文件中包含的修订历史记录。资源可能会在不通知的 情况下更改。我公司将不对使用此产品及其使用而导致的专利或第三方知识产权的侵权负责